

**APPLICATION**  
**FOR**  
**UNITED STATES LETTERS PATENT**

**TITLE:** **OBJECT-BASED CODING AND DECODING APPARATUSES  
AND METHODS FOR IMAGE SIGNALS**

**APPLICANT:** **SUNG MOON CHUN, JIN HAK LEE, JOO HEE MOON, GWANG  
HOON PARK, JAE KYOON KIM, JAE-WON CHUNG**

"EXPRESS MAIL" Mailing Label Number EL010093744 US

Date of Deposit November 19, 1998

I hereby certify under 37 CFR 1.10 that this correspondence is being deposited with the United States Postal Service as "Express Mail Post Office To Addressee" with sufficient postage on the date indicated above and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231.

J. C. Morrissey  
J. C. Morrissey

OBJECT-BASED CODING AND DECODING APPARATUSES AND METHODS FOR  
IMAGE SIGNALS

CL BACKGROUND OF THE INVENTION

5

P+b 1. Field of the Invention

10 P The present invention relates to image signal compression coding and decoding, and more particularly to an apparatus for and a method of coding image signals, wherein upon scanning transform coefficients of an input image signal in a shape-adaptive transform coding, only segments containing such shape-adaptive transform coefficients are scanned, thereby reducing the quantity of data being transmitted. The present invention also relates to an apparatus for and a method of decoding image signals, 15 wherein an inverse scanning for transform coefficients of a bitstream encoded in the above-mentioned manner is carried out upon decoding the bitstream, taking into consideration only segments containing those transform coefficients.

P+b<sup>20</sup> 2. Description of the Prior Art

P Compression coding and decoding of image signals makes it

50 + CL This application is a continuation-in-part of 08/578,142  
filed on 12-26-95 now  
abandoned.

possible to achieve transmission of image information while reducing the memory capacity required to store image signals.

Thus, such compression coding and decoding techniques are very important techniques in multimedia industries involving applications such as storage and transmission of image signals.

Meanwhile, a standardization for information compression schemes has been necessary for extension of multimedia industries and information compatibility. To this end, various image standardization schemes associated with a variety of applications have been proposed. For example, as representative image coding and decoding standardization schemes, there are H.261 of International Telecommunication Union - Telecommunication Standardization Sector (ITU-T, the successor of CCITT) for video phone or video conference services using integrated services digital networks (ISDN), and H.263 of ITU-T for transmission of video information using public switched telephone networks (PSTN), MPEG-1 proposed by Moving Picture Experts Group (MPEG) of International Standardization Organization/International Electrotechnical Commission Joint Technical Committee 1/Sub Committee 29/Working Group 11 (ISO/IEC JTC1/SC29/WG11) for storage media, and MPEG-2 for high quality digital broadcasting associated with high definition

televisions (HDTV) and enhanced digital television(EDTV). Standardization for compressive coding of still image signals also has been made by, for example, Joint Photographic Coding Experts Group (JPEG) of ISO/IEC JTC1/SC29/WG1.

5 In most conventional image signal coding schemes, the entire segment of a rectangular frame or picture is encoded.

Such schemes are called "frame-based coding". In such image signal coding schemes, texture information of all pixels included in a frame, namely, luminance and chrominance, is  
10 encoded and transmitted.

Recently, the demands for multimedia products have been increased which have functions of coding or manipulating only particular regions - or object - of a frame interested or needed to the user without coding the entire region of the frame. To  
15 this end, active research has recently been conducted for object-based coding schemes adapted to encode only arbitrary shape region of a frame, as a substitute for frame-based coding schemes adapted to encode the entire region of a frame. Figs. 1 and 2 illustrate test images for explanation of such an  
20 object-based coding scheme, respectively. Fig. 1 is a frame showing features of two children playing with a ball in an arbitrary space (background). Where information, only

associated with the children and ball, of the image is to be encoded and transmitted coding of such information can be achieved using the object-based coding scheme, that is, only texture information values of pixels associated with the children and ball are encoded and transmitted. In this case, the regions respectively associated with the children and ball are designated to be an object, whereas the remaining region of the picture other than the object is considered to be a background.

For coding of the picture shown in Fig. 1 using the object-based coding scheme, all pixels included in the frame should be distinguished into those associated with the children and ball and those associated with the background in an encoder and a decoder. This information is referred as shape information of the object. In order to allow the decoder to recognize the shape information, the encoder should efficiently encode the shape information and then transmit the shape information to the decoder. For thus, the object-based encoder and decoder have a most remarkable difference from the frame-based encoder and decoder in that they include a shape information encoder and a shape information decoder, respectively.

Fig. 2 shows shape information included in the image information where only the children and ball are considered to be

an object. In this case, the pixels associated with the children and ball have shape information bearing a bright value whereas the pixels associated with the background have shape information bearing a dark value. Such shape information of pixels assigned with different values to distinguish those of the pixels associated with the object from those associated with the background is called a "binary mask". Shape information may also be expressed by a contour indicative of the boundary between the background and the object. A transformation can be made between the shape information in the form of a binary mask and the shape information in the form of a contour. That is, the shape information having the form of a binary mask can be expressed into contour information by carrying out a contour extraction. On the other hand, a contour filling is carried out for obtaining a binary mask from contour information.

Representative examples of frame-based coding schemes include H.261 and H.263 of ITU-T, MPEG-1 and MPEG-2 of ISO/IEC JTC1/SC29/WG11, and JPEG of ISO/IEC JTC1/SC2 all being standardized schemes. On the other hand, representative examples of object-based coding schemes include MPEG-4 of ISO/IEC JTC1/SC29/WG11 and JPEG2000 of ISO/IEC JTC1/SC29/WG11.

Transform coding is the most widely used coding method in

well-known compressive coding schemes for image signals. In such a transform coding, an image signal is transformed to transform coefficients - or frequency coefficients and low frequency components are mainly transmitted while suppressing transmission of high frequency components. This scheme has an advantage of a high compression ratio while minimizing the degradation of picture quality. Examples of such a transform coding scheme include a discrete Fourier transform (DFT), a discrete cosine transform (DCT), a discrete sine transform (DST), and a Walsh-Hadamard transform (WHT).

Of such transform schemes, DCT is a scheme providing a superior compactness of image signal energy on low-frequency components. In other words, DCT provides a superior picture quality over other transform schemes, in spite of only using a reduced number of low frequency transform coefficients. In addition, there is a fast algorithm for DCT. By virtue of such an advantage, DCT has been used in various image coding standardization schemes such as H.261, H.263, MPEG-1, MPEG-2, MPEG-4, and JPEG.

Research of such transform coding schemes has been made with respect to image signals in blocks each consisting of a set of

pixels (picture elements or pels) with a certain size. In accordance with transform coding schemes developed, a rectangular frame is divided into a plurality of blocks having the same size. A transform coding is then carried out for each block.

5 In the case of an object-based coding scheme only texture information included in objects is encoded, as compared to frame-based coding scheme in which texture information of all pixels included in a rectangular frame is completely encoded. In such an object-based coding scheme, accordingly, it is required  
10 to conduct a transform coding only for image signal of some pixels of blocks associated to the object. Fig. 3 illustrates an object having an arbitrary shape in a frame divided into a plurality of blocks. In Fig. 3, each square region is indicative of one block.

Dark region is indicative of a set of pixels associated with the  
15 object. In Fig. 4, transparent blocks correspond to blocks of Fig. 3 not to be encoded because of including no object pixel, respectively. The black blocks of Fig. 4 are indicative of blocks which are to be transformed by one of the known transform coding schemes because all pixels thereof are object pixels. The  
20 gray blocks of Fig. 4 are indicative of blocks each including both the object pixels and the non-object pixels, thereby requiring a transform coding only for texture information of a part of pixels



thereof. In the following description, blocks corresponding to such gray blocks are referred to as "boundary blocks". This scheme, in which a transform coding is not conducted for the entire pixels of each square block, but conducted for a part of pixels included in each square block, is called a "shape-adaptive transform coding".

In a representative shape-adaptive transform coding scheme, each block which is a coding unit consists of 8x8 pixels. Namely, blocks include 8 lines per block and 8 pixels per line. In accordance with the scheme, texture signal of object pixels to be encoded are processed by an one-dimensional DCT in a vertical direction and then in a horizontal direction.

Referring to Fig. 5A, an 8x8 block is illustrated which has an object region to be encoded. In Fig. 5A, gray pixels are pixels associated with objects. For processing an shape-adaptive DCT coding for texture signal of object pixels to be encoded, a re-arrangement of pixels is carried out by vertically shifting those object pixels to the upper border of the block, thereby filling that border, as shown in Fig. 5B. In this state, one-dimensional DCT is performed in a vertical direction (indicated by thick lines in Fig. 5) for texture information of each column including object pixels. As a result, transform coefficients of

one-dimensional DCT are generated, as shown in Fig. 5C. The solid circles in Fig. 5C denote positions of mean values of vertical one-dimensional DCT, namely, direct current (DC) values, respectively. After completing the vertical one-dimensional DCT as shown in Fig. 5D, a pixel re-arrangement is conducted again by shifting again the object pixels to the left border of the block.

Thereafter, one-dimensional DCT is performed in a horizontal direction for the transform coefficients included in each of rows, which comprise at least one transform coefficient, as shown in Fig. 5E. Fig. 5F shows positions of transform coefficients completing the one-dimensional DCT in both the vertical and horizontal directions. This procedure, namely, the transform, in which one directional DCT is carried out in a successive manner in the vertical and horizontal directions, is called a "shape-adaptive DCT". It should be noted that the positions of transform coefficients resulting from the shape-adaptive DCT may not be coincide with those of input object pixels (or input shape information) and that the positions of those transform coefficients are determined only based on the input shape information. The number of transform coefficients resulting from the shape-adaptive DCT is equal to the number of object pixels, as in the conventional block-wised DCT schemes.

Fig. 6 illustrates a block diagram of a conventional shape-adaptive image signal coding apparatus (=texture information encoding part 24) which utilizes the above mentioned shape-adaptive DCT. This apparatus 24 receives, as an input thereof, shape information on a block basis having a  $M \times N$  size ( $M$  and  $N$  are integer values larger than zero) and texture information of object pixels in the form of a block having the same size as the shape information block. In the case of Figs. 5A to 5F, block of  $M=8$  and  $N=8$  is inputted. The apparatus 24 generates an output in the form of a bitstream. The outputted bitstream is transmitted to a receiver. Otherwise, the bitstream may be transmitted to a multiplexer (MUX) so that it is multiplexed with other signals, for example, bitstreams of shape information.

An shape-adaptive DCT part 10 first performs a shape-adaptive DCT for input texture information of object pixels, based on input shape information, thereby outputting transform coefficients which are positioned at the upper left portion of an associated block, as shown in Fig. 5F. For these transform coefficients, a quantization is conducted for data compression in a quantization part 11. As a result, quantized transform coefficients are outputted from the quantization part 11. The

transform coefficients from the quantization part 11 are then transmitted to a scanning part 12 which, in turn, carries out a scanning procedure for arranging the received transform coefficients into a one-dimensional array. Various scanning methods applicable to blocks of  $M=8$  and  $N=8$  are illustrated in Figs. 7A to 7C. Fig. 7A illustrates a zig-zag scanning order most widely used. In Fig. 7A, the numerals indicated on respective portions of the block are indicative of the scanning order of corresponding transform coefficients upon arranging those transform coefficients in a one-dimensional array. The scanning methods of Figs. 7A to 7C can be selectively used in accordance with the characteristics of input image signals to be subjected to a transform coding. These scanning methods are also used in MPEG-2 and MPEG-4 schemes. Blocks, which are processed by the shape-adaptive DCT, may include segments containing no transform coefficient, as shown in Fig. 5F. In accordance with a conventional schemes, a scanning operation is carried out for the entire segment of a block in a sequential manner according to a well-known, predetermined scanning order while setting transform coefficient values of segments containing no transform coefficient to "zero". That is, all segments - 64 transform coefficients in the case of an  $8 \times 8$  block - are sequentially

12

scanned using one of the known scanning methods, irrespective of whether or not the segments to be scanned contain transform coefficients. The resultant transform coefficients arranged in a one-dimensional array are subjected to a variable-length coding in a variable-length coding part 13. The resultant signal in the form of a bitstream is then transmitted to an MUX or receiver.

The variable-length coding part 13 receives, as an input thereof, the DCT coefficients outputted from the scanning part 12 and carries out a variable-length coding for the transform coefficients arranged in a one-dimensional array in a sequential manner.

Now, the variable-length coding for transform coefficients will be described in conjunction with H. 263 which is a representative of conventional variable-length coding schemes.

In accordance with this scheme, EVENTS of transform coefficients with values not being "zero" are first derived. For the derive EVENTS, corresponding bitstreams are then sought from a given variable-length coding (VLC) table. Thereafter, the sought codes are sequentially outputted. Each EVENT consists of a combination of three kinds of information, namely, a LAST indicative of whether or not the transform coefficient being

currently encoded is the last non-zero transform coefficient, a  
RUN indicative of the number of successive zero transform  
coefficients preceding the current non-zero coefficient and a  
LEVEL indicative of the magnitude of the current transform  
5 coefficient.

Such EVENTS, which are combined and defined as mentioned  
above, can be entropy-coded through a variable-length coding  
such as Huffman coding or arithmetic coding. This is, a smaller  
amount of bits are allocated for EVENTS exhibiting a higher  
10 occurrence probability. On the other hand, a larger amount of  
bits are allocated for EVENTS exhibiting a lower occurrence  
probability. Accordingly, it is possible to achieve coding of  
EVENTS using a considerably reduced number of bits, as compared  
to a fixed-length coding (FLC).

15 A part of a VLC table that used for H.263. is illustrated in  
Table 1.

*MP*



24      0      3      3      11      0000 0011 01s

המחיר המלא של המוצר: ₪ 1,200.00

P In the Table 1, the first column represents indexes for  
5 distinguishing EVENTS from one another. The second column  
represents LASTs. LAST=0 denotes that coefficient to be coded  
is not the last non-zero transform coefficient whereas LAST=1  
denotes that the coefficient is the last one. The third column  
represents RUNs. The fourth column represents LEVELs indicative  
10 of values of transform coefficients. The fifth column  
represents the number of bits generated for each EVENT. The last  
column represents a bitstream generated for each EVENT. In the  
last column, "s" is indicative of the sign of each LEVEL. A s  
of "0" ( $s = 0$ ) is indicative of the fact that the associated LEVEL  
15 is a positive number whereas a s of "1" ( $s = 1$ ) is indicative of  
the fact that the associated LEVEL is a negative number.

With regard to the occurrence probability of EVENTS, it should be noted that EVENTS exhibit a lower occurrence probability at greater RUN values and a higher occurrence probability at smaller RUN values. Where the variable-length coding is conducted, taking RUNs into consideration, accordingly, a larger amount of bits are allocated for an EVENT with a greater



RUN value whereas a smaller amount of bits are allocated for an EVENT with a smaller RUN value. Referring to the VLC table of H.263 as shown in Table 1, such a feature can be clearly understood.

This will be exemplarily described in conjunction with EVENTS

5 (INDEX = 1, 13, 19) respectively having RUNS of 0, 1, 2, along with  
LAST = 0 and LEVEL = 2. For the EVENT bearing INDEX = 19 (LAST  
= 0, RUN = 2, and LEVEL = 2), nine bits are allocated. Seven bits  
are allocated for the EVENT bearing INDEX = 13 (LAST = 0, RUN =  
1, and LEVEL = 2). On the other hand, five bits are allocated for  
10 the EVENT bearing INDEX = 1 (LAST = 0, RUN = 0, and LEVEL = 2).

Thus, a larger amount of bits are allocated at a greater RUN value  
under the condition in which the LAST and LEVEL values are fixed.

15 P Known shape-adaptive DCT coding schemes may use the above  
mentioned transform coefficient VLC method or VLC table. This  
will be exemplarily described in conjunction with Figs. 8A to 8E.

Fig. 8A shows the result obtained after carrying out a shape-  
adaptive DCT and quantization for an image signal in the form of  
an 8x8 block. In Fig. 8A, the dark segments correspond to object  
pixels of the block, respectively. Accordingly, the dark  
20 segments correspond to segments containing transform  
coefficients generated due to the object pixels. The remaining

bright segments are indicative of segments containing no transform coefficient, thereby being set with a transform coefficient value of "0". In each dark segment, "Xij" represents a transform coefficient positioned at an i-th position in a horizontal direction and a j-th position in a vertical direction in 8x8 block. When all transform coefficients of the block are scanned in a zig-zag scanning order, they are arranged in the order of X11, X12, X21, X31, X22, X13, X14, 0, X32, X41, X51, X42, 0, 0, X15, X16, 0, 0, 0, X52, X61, X71, 0, 0, ..., and 0. If the transform coefficient X71 is not zero, then the variable-length coding can be carried out only for segments positioned within the region defined by the thick solid line of Fig. 8B. Fig. 8C illustrates the case in which two transform coefficients X32 and X42 are zero whereas the remaining transform coefficients having non-zero values, respectively. When the transform coefficient X41 is encoded in this case, its LAST value is zero because it is not the last one of non-zero transform coefficients in the block. In this case, LEVEL and RUN values are X41 and 2, respectively. With regard to the transform coefficient X41, such an increase in RUN value caused by the transform coefficient X32 having a value of zero is reasonable because the zero value of the transform coefficient X32 is generated in accordance with a

signal information of associated object. However, the transform coefficient value of zero existing between the transform coefficients X14 and X32 is a value not generated in accordance with the object information transform, but given for a segment  
5 containing no transform coefficient. Accordingly, transmission of such information is unnecessary and rather results in an increase in RUN value. As a result, there is a disadvantage in that an increased number of bits is generated. This causes a reduction of the coding efficiency of the  
10 shape-adaptive DCT coding.

Although problems involved in the conventional shape-adaptive DCT coding, which is a representative shape-adaptive transform coding scheme, have been described, other shape-adaptive transform coding schemes also have the same problems.

15 That is, the conventional shape-adaptive transform coding schemes have a problem in that an addition of unnecessary values of zero is involved in the scanning procedure.

Meanwhile, a variety of VLC coding schemes for carrying out a VLC for transform coefficients have been used. Although the  
20 VLC table of H.263 has been exemplified in the above description, a VLC table consisting of a combination of only RUN and LEVEL is used in the cases of JPEG, MPEG-1, and MPEG-2. In this case,

however, the above mentioned problem namely, reduction of coding efficiency, also occurs because an increase in RUN value results in an increase in the number of coding bits occurs.

5 *CL* SUMMARY OF THE INVENTION

*P* Therefore, an object of the invention is to overcome the above mentioned problems and to provide an object-based coding apparatus and method for image signals, wherein upon scanning  
10 shape-adaptive transform coefficients of an input image signal transformed in accordance with a shape-adaptive transform for an object-based coding thereof, only segments containing such shape-adaptive transform coefficients are scanned, thereby reducing the quantity of data being encoded.

15 *P* Another object of the invention is to provide an object-based decoding apparatus and method for image signals capable of effectively decoding image data transmitted after being encoded in accordance with a coding method of the present invention.

20 *DR + CL* BRIEF DESCRIPTION OF THE DRAWINGS

*P* Other objects and aspects of the invention will become

apparent from the following description of embodiments with reference to the accompanying drawings in which:

P Fig. 1 is a view illustrating a test image for explanation of an object-based coding scheme;

5 P Fig. 2 is a view illustrating the shape information of the test image shown in Fig. 1;

P Fig. 3 is a schematic view illustrating object blocks for a shape-adaptive transform coding;

10 P Fig. 4 is a schematic view for explanation of the shape-adaptive transform coding for each block of Fig. 3;

Figs. 5A to 5F are schematic views respectively illustrating successive steps involved in a general shape-adaptive DCT procedure;

15 Fig. 6 is a block diagram illustrating a conventional shape-adaptive image signal coding apparatus;

Figs. 7A to 7C are schematic views for explanation of scanning methods to which the present invention is applicable, respectively;

20 Figs. 8A to 8E are schematic views for explanation of a VLC method for quantized transform coefficients, respectively;

Fig. 9 is a block diagram illustrating an object-based image signal encoder according to the present invention;

P Fig. 10 is a block diagram illustrating an object coding unit according to the present invention;

Fig. 11 is a block diagram illustrating an object-based coding of image signals in accordance with the present invention;

5 Figs. 12A and 12B are block diagrams respectively illustrating different embodiments of a shape-adaptive scanning part according to the present invention;

Fig. 13 is a block diagram illustrating an object-based image signal decoder according to the present invention;

10 Fig. 14 is a block diagram illustrating an object decoding part according to the present invention;

Fig. 15 is a block diagram illustrating an apparatus for object-based decoding of image signals in accordance with the present invention; and

15 Figs. 16A and 16B are block diagrams respectively illustrating different embodiments of a shape-adaptive inverse scanning part according to the present invention.

DE CL DESCRIPTION OF THE PREFERRED EMBODIMENTS

20

P Figs. 9 to 11 illustrate respective object-based image signal coding systems to which the present invention is

applicable. Fig. 9 is a block diagram illustrating a general object-based image signal coding system. This system is adapted to divide an input image signal into object each having arbitrary shape information and to carry out a coding operation for each of the object. An input image signal is first applied to an object formation part 1 included in the objected-based image signal encoder. In the object formation part 1, the input image signal is divided into each object. The object formation part 1, then derives shape information and texture information for each object. The resultant signals for each object are applied to an object coding part 2 which, in turn, conducts a coding operation for those signals. This coding operation of the object coding part 2 is sequentially carried out for all objects (2-1, 2-2, ..., and 2-n). Outputs resulting from the object coding for all objects, namely, bitstreams are then multiplexed in a multiplexer (MUX) which, in turn, sends the resultant signal to a receiver or storage media.

Fig. 10 illustrates the configuration of an object coding unit included in the object coding part 2 of Fig. 9. Although the object coding part 2 is shown in Fig. 9 as consisting of a plurality of object coding units, it practically includes a single object coding unit which repeatedly performs a coding

operation by  $n$  times ( $2-1$ ,  $2-2$ , ..., and  $2-n$ ) for  $n$  objects.

Signal information of each object, which is inputted at the object coding unit, are divided into shape information and texture information. These shape information and texture  
5 information are first inputted in a shape information coding part 20 and a motion estimation part 21, respectively.

The shape information coding part 20 serves to encode the shape information of the associated object. The resultant reconstructed shape information is then applied to a motion  
10 estimation part 21, motion compensation part 22 and a texture information coding part 24. Thus, the operation of each part is carried out on an object basis. Meanwhile, a shape information bitstream, which is another output from the shape information coding part 20, is inputted to a multiplexer 25.

15 The reconstructed shape information controls motion estimation, motion compensation, texture information coding. In order to control a decoding apparatus in the same way as above, the reconstructed shape information of an encoder should be coincide with a reconstructed shape information in the form of  
20 shape information bitstreams received by the decoding apparatus. On the other hand, in case that lossless coding is carried out in the shape information coding part, the reconstructed shape



information is identical with the input shape information. In case of lossy coding, the reconstructed shape information is different from the input shape information. Therefore, controlling process for object-based coding of image signal is performed by using not the input shape information but the reconstructed shape information. The shape information disclosed hereinafter is reconstructed shape information unless otherwise noted.

The motion estimation part 21 serves to estimate motion information of the texture information of the current object using the texture information of the current object and the texture information of the previous object stored in a previous reconstructed object information memory 27. The motion information is input to the motion compensation part 22 for a motion compensated prediction. The estimated motion information is efficiently encoded and then the resultant motion information bitstream is input to the multiplexer 25. The motion compensation part 22 carries out a motion compensated prediction using the motion information derived by the motion estimation part 21 and the previous reconstructed object texture information stored in the previous reconstructed object information memory 27.

A subtractor 23 calculates a prediction error, namely, a difference between the input texture information and the motion compensated prediction texture information derived by the motion compensation part 22. The resultant signal from the subtractor 5 23 is encoded in the texture information coding part 24. The resultant texture information bitstream from the texture information coding part 24 is applied to the multiplexer 25 and the reconstructed prediction error signal is applied to an adder 26. This adder 26 adds the reconstructed error signal to the 10 motion compensated prediction signal, thereby generating a reconstructed texture information signal of an associated object. This reconstructed texture information signal is stored in the previous reconstructed object information memory 27 so that it is used for coding of an object to be subsequently inputted.

15 Using the reconstructed shape information received from the shape information coding part 20, the texture information coding part 24 encodes the texture information of an associated object.

In the texture information coding part 24, the coding operation is not carried out for entire object, but carried out on a block 20 basis which is pixel set having a certain size, for example, a MxN size.

Meanwhile, although the texture information coding part of

Fig. 10 is illustrated as being adapted to encode prediction error signals, it may be possible to encode input texture information in place of such prediction error signals. In this regard, it is possible to achieve an improvement in coding efficiency by adaptively encoding a selected signal enabling more efficient coding thereof out of the prediction error signal and texture information signal. For example, where motion information estimation is inaccurately carried out, the resultant prediction error signal has an increased value. In this case, accordingly, it is preferred that the input texture information be encoded, because a smaller number of bits are generated. Where coding of input texture information is carried out, it is unnecessary to use an adder operation for adding the reconstructed texture information to the prediction signal. Therefore, the coding part generally includes a control unit for determining a suitable mode and carrying out a control based on the determined mode, even though not shown in Fig. 10.

Fig. 11 illustrates an apparatus for object-based coding of image signals in accordance with the present invention. This apparatus corresponds to the texture information coding part (24) of Fig. 10. As shown in Fig. 11, the object-based coding apparatus for image signals according to the invention

comprises:

P1 a shape information coding part for encoding shape information of an input image signal;

P1 a shape-adaptive transform part for carrying out a shape-adaptive transform for texture information of said input image signal, based on said shape information outputted from said shape information coding part;

P1 a shape-adaptive scan control part for forming a binary coefficient mask having the same transform coefficient distribution as that of an output signal from said shape-adaptive transform part, and generating a scan control signal in accordance with existence or nonexistence of a transform coefficient based on said binary coefficient mask; and

P1 a shape-adaptive scanning part for carrying out a scanning operation for an output from said shape-adaptive transform part, based on the associated control signal from said shape-adaptive scan control part.

P The shape-adaptive scan control part 240 of the object-based coding apparatus comprises:

P1 a coefficient forming unit 241 adapted to form a binary coefficient mask for sorting segments containing transform coefficients from segments containing no transform coefficient

which has the same transform coefficient distribution as that of an output signal from said shape-adaptive transform part; and

5 P1 a control signal generation unit 242 adapted to generate a skip signal for skipping segments containing no transform coefficient from the scanning operation of said shape-adaptive scanning part.

10 P The shape-adaptive scan control part 240 receives reconstructed shape information from the shape information coding part 20 of Fig. 10, thereby generating a control signal for sorting segments containing transform coefficients from segments containing no transform coefficient so as to control a scanning operation in such a manner that the segments containing transform coefficients are scanned in a scan order while the segments containing no transform coefficient are excluded from  
15 the scan order.

20 P The coefficient forming unit 241 is adapted to transform the input reconstructed shape information in the same manner as in a shape-adaptive transform coding, thereby forming a coefficient mask which denotes a region of segments having a transform coefficient (transform coefficient region) so as to sort segments containing transform coefficients from segments containing no transform coefficient. The scan control signal generation unit

242 serves to scan the coefficient mask in the same manner as in the scanning of transform coefficients and to generate a signal indicative of whether or not the currently scanned mask corresponds to the transform coefficient region.

- 5     p The apparatus further includes a shape-adaptive scanning part 245 which scans quantized coefficients contained in the segments containing transform coefficients while excluding the segments containing no transform coefficient, thereby skipping them, in response to the control signal generated from the
- 10 shape-adaptive scan control part 240.

- 15     The shape-adaptive scanning part(245) according to the present invention also receives transform coefficients outputted from a shape-adaptive transform unit(243) and conducts a scanning operation for arranging those transform
- 20 coefficients in a one-dimensional array. During the scanning operation, the shape-adaptive scanning part receives a control signal - a signal indicative of whether or not the currently scanned segment contains an associated transform coefficient - from the shape-adaptive scan control unit, in order to exclude segments containing no transform coefficient from the scan order, namely, to prevent zero coefficients of those segments from being included in the one-dimensional array.

P In other embodiment of the present invention, the shape-adaptive scanning part 245 comprises:

P1 a scanning unit 245-1 adapted to scan the entire segment including segments containing shape-adaptive transform coefficients and segments containing no transform coefficient, but respectively filled with coefficients of a predetermined value; and

0916997-26856160  
10 P1 a switching unit 245-2 adapted to receive an output signal from said scanning unit and to switch off said output signal from said scanning unit, based on said skip signal from said control signal generation unit, when said output signal is associated with a segment containing no transform coefficient.

P In accordance with the present invention, therefore, it is possible to reduce the number of zero coefficients unnecessarily inserted irrespective of non-existence of transform coefficients in the case of the conventional scanning methods. This results in an advantage of an improvement in coding efficiency.

P Now, the operation of the object-based image signal coding apparatus of Fig. 11 according to the present invention, which corresponds to the texture information coding part 24 of Fig. 10, will be described in detail. When a boundary block as shown in

Fig. 4 is inputted at the input stage of a shape-adaptive transform unit 243, it is processed by the well-known shape-adaptive transform, so that the shape-adaptive transform unit 243 outputs shape-adaptive transform coefficients. In this case, the texture information signal inputted at the shape-adaptive transform unit 243 may be a prediction error signal as used in the case of Fig. 10. Alternatively, an input texture information signal may be inputted where the prediction error signal has a large value. Such an input mode selection has no direct relation with the present invention. The shape-adaptive transform unit 243 also receives reconstructed shape information outputted from the shape information coding part 20 of Fig. 10 in order to determine which pixels correspond to object pixels. The number of transform coefficients outputted from the shape-adaptive transform unit 243 is equal to the number of object pixels.

Where the transform coding used is the shape-adaptive DCT, the transform coefficients are arranged in a manner as described in conjunction with Fig. 5. Referring to this example, it can be found that the transform coefficients outputted from the shape-adaptive transform unit 243 have a different arrangement from the shape information inputted at the same unit 243. Accordingly, it is necessary to change the arrangement of the



input shape information so that it is identical to that of the transform coefficients. This arrangement change is carried out in the coefficient mask forming unit 241. This will be described in more detail. The input of the coefficient mask forming unit 241 is the input shape information whereas the output of the same unit 241 is shape information having an arrangement identical to the arrangement of the transform coefficients outputted from the shape-adaptive transform unit 243. That is, the coefficient mask forming unit 241 forms a coefficient mask for determining whether or not the currently scanned segment contains an associated transform coefficient. The coefficient mask output from the coefficient mask forming unit 241 is applied to the scan control signal generation unit 242 via an output stage thereof.

Based on such shape information, the scan control signal generation unit 242 controls the shape-adaptive scanning part 245.

P The transform coefficients from the shape-adaptive transform unit 243 are applied to a quantization part 244 which, in turn, carries out a quantization for the received transform coefficients. The quantized transform coefficients are transmitted to the shape-adaptive scanning part 245 which, in turn, arranges the received transform coefficients in a one-

dimensional array. The transform coefficients arranged in a one-dimensional array are applied to a variable-length coding part (VLC) 246 which, in turn, conducts a coding operation for the received transform coefficients, thereby outputting an associated bit stream. In the case of the well-known scanning methods, a transform coefficient scanning operation is performed for the entire segment of a block, as shown in Figs. 7A to 7C. In the shape-adaptive transform, however, only the transform coefficients respectively associated with pixels included in the object region are transmitted. In this case, the arrangement of the transform coefficients outputted from the shape-adaptive transform unit 243 or quantization part 244 is changed depending on the shape information. Accordingly, the control signal generation unit 242 generates a signal indicative of whether or not the currently scanned mask region corresponds to the transform coefficient region, based on the shape information outputted from the coefficient mask forming unit 241, while conducting its scanning operation in the same manner as in the shape-adaptive scanning part 245, based on the shape information outputted from the coefficient mask forming unit 241. As mentioned hereinbefore, the shape information outputted from the coefficient mask forming unit 241 has the same arrangement as that

of the transform coefficients outputted from the shape-adaptive transform unit 243. Therefore, the scan control, which is carried out based on such shape information, makes it possible to effectively eliminate unnecessary information possibly generated in the shape-adaptive transform coding. Thus, there is an advantage of an improvement in coding efficiency.

Abstract = 20350760  
p Figs. 12A and 12B illustrate embodiments of the shape-adaptive scanning part 245 according to the present invention, respectively. In the case of Fig. 12A, the shape-adaptive scanning part 245 includes a scanning unit 245-1 and a switching unit 245-2. The shape-adaptive scanning unit 245-1 is configured to operate in the same scanning manner as in the conventional scanning method of Figs. 7A to 7C. The switching unit 245-2 serves to carry out its switching operation in accordance with a control signal received from the shape-adaptive scan control unit 245-1. Where the control signal applied to the switching unit 245-2 is indicative of a segment containing no transform coefficient, the switching unit 245-2 is switched off. The switching unit 245-2 is also switched on when the control signal applied thereto is indicative of a segment containing a transform coefficient. In accordance with such an operation of the switch controlled in response to the control

signal, the shape-adaptive scanning part generates its output only for segments containing transform coefficients. This will be described in more detail in conjunction with Fig. 8C. Assuming that the scanning method used is a zig-zag scanning method, the shape-adaptive scanning part outputs X11, X12, X21, X31, X22, X13, X14, 0, 0, X41, X51, 0, 0, 0, X15, X16, 0, 0, 0, X52, and X71. The control signal generation unit of the shape-adaptive scan control part, which receives the transform coefficient position information as shown in Fig. 8C, scans all segments in the same order as in the zig-zag scanning carried out in the shape-adaptive scanning. When the control signal generation unit scans a segment containing a transform coefficient, it generates a control signal for switching on the switch.

P The control signal generation unit 242 also outputs a control signal for switching off the switching unit 245-2 when it scans a segment containing no transform coefficient. Thus, the switching unit 245-2 outputs X11, X12, X21, X31, X22, X13, X14, 0, X41, X51, 0, X15, X16, X52, and X71 while receiving inputs of X11, X12, X21, X31, X22, X13, X14, 0, 0, X41, X51, 0, 0, 0, X15, X16, 0, 0, 0, X52, and X71.

P On the other hand, the object-based image signal coding

apparatus shown in Fig. 12B includes a shape-adaptive scanning part 245 configured to control its scanning operation by a control signal, as compared to the case of Fig. 12A in which the object-based image signal coding apparatus includes a scanning unit 245-1 configured to operate in the same scanning manner as in the conventional scanning method, and a switch controlled by a control signal. In the case of Fig. 12B, a new scanning scheme is defined and used. That is, the shape-adaptive scanning part of Fig. 12B itself operates to skip segments containing no transform coefficient while basically operating in the same manner as in the conventional scanning method. Assuming that this shape-adaptive scanning part 245 basically operates in a zig-zag scanning fashion and receives the transform coefficient position information as shown in Fig. 8C, it carries out a scanning operation in accordance with a new scanning scheme shown in Fig. 8D, in response to a control signal applied thereto. The shape-adaptive scanning part 245 of Fig. 12B may also basically use the scanning scheme as shown in Fig. 7B or 7C. Thus, the scanning scheme intended in this embodiment may be determined in accordance with the input shape information and the basic scanning scheme used. Of course, both the embodiments of Figs. 12A and 12B provide the same result where the same input shape

information and the same basic scanning scheme are used.

P Although not shown in Fig. 11 and Fig. 12, the texture information coding part should include a unit adapted to reconstruct an encoded texture information signal. Generally, this unit carries out an inverse quantization procedure and an inverse transform procedure. The resultant reconstructed texture information signal is applied to the adder of Fig. 10.

P Figs. 13 and 14 illustrate an object-based image decoding system in accordance with the present invention. Fig. 13 illustrates a block diagram schematically illustrating an object-based image decoding system according to the present invention. A bitstream, which is received in the object-based image decoding system, is divided into bitstreams respectively associated with objects. The resultant object bitstreams are decoded in an object decoding part 32 in association with objects, respectively. The resultant reconstructed object signals from the object decoder 32 are composed by a composition part 33, thereby generating and displaying a single image signal.

P Fig. 14 is a block diagram illustrating a detailed configuration of the object decoding part 32 according to the present invention. Although the object decoding part 32 is shown in Fig. 13 as consisting of a plurality of object decoding units,

it practically includes a single object decoding unit which repeatedly performs a decoding operation by n times (32-1, 32-2, ..., and 32-n) for n objects. The illustration of Fig. 13 is only to emphasize individual decoding operations of the object decoding part 32 for objects. A bitstream, which is received in the object decoding part 32, is demultiplexed into a motion information bitstream, a shape information bitstream, and a texture information bitstream via a demultiplexer (DEMUX) 41.

The separated bitstreams are then applied to decoding parts 42 to 44, respectively. The shape information decoding part 43, which receives the shape information bitstream, generates reconstructed shape information. This reconstructed shape information is applied the texture information decoding part 44.

The reconstructed shape information is also applied to a motion compensation part 45. Thus, decoding is carried out for each object. That is, reconstruction of pixels only included in the object region is possible. The texture information decoding part 44 receives the texture information bitstream, thereby conducting a texture information decoding operation. In order to decode only the texture information associated with the object region, the texture information decoding part 44 also receives the reconstructed shape information and uses it upon decoding the

texture information. The motion information decoding part 42 receives the motion information bitstream, thereby conducting a motion information decoding operation. The motion compensation part 45 carries out a motion compensated prediction, based on the motion information outputted from the motion information decoding part 42 and the previous texture information from a previous reconstructed object memory part 46. Of course, the operation of the motion compensation part 45 is carried out only in association with the object region. To this end, the reconstructed shape information outputted from the shape information decoding part 43 is also applied to the motion compensation part 45. This reconstructed shape information is identical to the reconstructed shape information outputted from the shape information coding part of Fig. 10. A motion compensated prediction signal outputted from the motion compensation part 45 is added to the reconstructed texture information from the texture information decoding part 44 in an adder 47, thereby recovering the associated object. The recovered object is stored in the previous reconstructed object memory 46 so that it is subsequently used upon decoding of the next frame. The recovered object is also applied to a composition part so that it is composed with other objects, thereby



reproducing an image signal.

P Fig. 15 is a block diagram illustrating an apparatus for shape-adaptive decoding of image signals in accordance with the present invention. This apparatus corresponds to the texture information decoding part 44 of Fig. 14. As shown in FIG. 15, the object-based decoding apparatus for image signals according to the invention comprises:

66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227  
2228  
2229  
2230  
2231  
2232  
2233  
2234  
2235  
2236

a shape-adaptive inverse transform for the transform coefficients inversely scanned by said shape-adaptive inverse scanning part, based on said decoded shape information outputted from said shape information decoding part, thereby  
5 reconstructing texture information of an original image.

10 P The apparatus includes a shape-adaptive inverse scan control part 440 for receiving reconstructed shape information outputted from a shape information decoding part 43, thereby generating a control signal for sorting segments containing transform coefficients from segments containing no transform coefficient so as to control an inverse scanning operation in such a manner that the segments containing transform coefficients are scanned in the well-known scan order while the segments containing no transform coefficient are excluded from the scan  
15 order.

20 P The shape-adaptive inverse scanning part 444 of the apparatus which inversely the segments containing transform coefficients while excluding the segments containing no transform coefficient, in response to the control signal generated from the shape-adaptive inverse scan control part 440.

P The shape-adaptive inverse scan control part 440 operates in the same manner as the shape-adaptive scan control part 240 of

Fig. 11. That is, the shape-adaptive inverse scan control part 440 includes a coefficient mask forming unit 441 adapted to transform the input reconstructed shape information in the same manner as in the shape-adaptive transform coding, thereby forming a coefficient mask which denotes a region of segments having a transform coefficient (transform coefficient region) so as to sort segments containing transform coefficients from segments containing no transform coefficient, and a control signal generation unit 442 adapted to scan the coefficient mask in the same manner as in the scanning of transform coefficients and to generate a signal indicative of whether or not the currently scanned mask segment corresponds to the transform coefficient region.

*P* The shape-adaptive inverse scanning part 444 according to the present invention also receives transform coefficients outputted from a variable-length decoding unit 443 and conducts a inverse scanning operation for arranging those transform coefficients in the form of a two-dimensional signal. During the inverse scanning operation, the shape-adaptive inverse scanning part 444 receives a control signal - a signal indicative of whether or not the currently scanned segment contains an associated transform coefficient - from the shape-adaptive

inverse scan control unit 440, in order to skip segments containing no transform coefficient from the scan order. In accordance with the present invention, therefore, it is possible to decode the bitstreams generated by way of reducing the number of zero coefficients unnecessarily inserted irrespective of non-existence of transform coefficients in the case of the conventional scanning methods.

10 P In accordance with an embodiment of the present invention shown in Fig. 16A, the shape-adaptive inverse scanning part 444 is configured so that during its scanning of segments processed by the variable-length decoding, it switches off outputting of scanned transform coefficient values associated with segments containing no transform coefficient, based on a skip signal from the control signal generation unit 442. In accordance with 15 another embodiment of the present invention shown in Fig. 16B, the shape-adaptive inverse scanning part 444 is configured so that during its scanning of segments, it excludes segments containing no transform coefficient from the scan order, thereby skipping them, based on a skip signal from the control signal generation 20 unit 442.

P In operation of the apparatus, a variable-length decoding part 443 receives a bitstream of texture information, thereby

outputting transform coefficients arranged in a one-dimensional array. The shape-adaptive inverse scan control part 440 has the same configuration as the shape-adaptive scan control part of Fig. 11. The coefficient mask forming unit 441 outputs a coefficient mask for determining whether or not the currently scanned segment contains an associated transform coefficient. This information is applied to the control signal generation unit 442 which, in turn, outputs a control signal indicative of which segments have no transform coefficient while inversely scanning the entire segment in the same manner as in the shape-adaptive inverse scanning part 444. The shape-adaptive inverse scanning part 444 conducts a procedure for re-arranging transform coefficients outputted from the variable-length decoding part 443. Thereafter, a dequantization for the transform coefficients is carried out in a dequantization part 445. The resultant transform coefficients are inversely transformed in a shape-adaptive inverse transform unit 446, thereby reconstructing texture information.

The shape-adaptive inverse scanning procedure according to the present invention will be exemplarily described in conjunction with Fig. 8C. The variable-length decoding part 443 outputs X11, X12, X21, X31, X22, X13, X14, 0, X41, X51, 0, X15,

X16, 0, X52, and X71 whereas the shape-adaptive inverse scanning part 444 generates outputs as shown in Fig. 8E. In Fig. 8E, the bright portions correspond to segments containing no transform coefficient. These segments are not subject to an object-based decoding. Even when these segments are filled with arbitrary values, the decoding part is not influenced by them. The inverse scanning unit 444-1 of Fig. 16A is configured to operate in the same scanning manner as in the conventional scanning method while using a switching unit 444-2 controlled by a control signal.

On the other hand, the shape-adaptive inverse scanning part of Fig. 16B uses a new inverse scanning scheme as shown in Fig. 8D.

The inverse scanning procedure according to the present invention may be carried out using a zig-zag scanning scheme or other scanning schemes.

As apparent from the above description, the present invention provides object-based coding and decoding apparatuses and methods for image signals, wherein upon scanning shape-adaptive transform coefficients of blocks transformed in accordance with a shape-adaptive transform, only segments containing such shape-adaptive transform coefficients are scanned. In the scanning operation, segments containing no transform coefficient are skipped. As a result, it is possible

to suppress transmission of unnecessary bits. Accordingly, there are redundant bits which can be used for an improvement in picture quality. This results in an improvement in the quality of image services.

5     P Although the preferred embodiments of the invention have been disclosed for illustrative purposes, those skilled in the art will appreciate that various modifications, additions and substitutions are possible, without departing from the scope and spirit of the invention as disclosed in the accompanying claims.

# THE FUTURE OF THE FUTURE